

| | | | | | |
|-------------------------|--|-----------------|-----|--------------|---------|
| Title: | DVR/NVR VGA, HDMI, BNC Output Comparison Chart | Version: | v.1 | Date: | 4/24/15 |
| Product: | Hikvision DVRs/NVRs | | | | |
| Action Required: | None, Information Only | | | | |

DVR/NVR VGA, HDMI, BNC Output Comparison Chart

DVR/NVR Firmware Version:

DS-7604NI-SE/P, DS-7608NI-SE/8P: V2.3.7 Build 140122

DS-9000, 9600, 7716:

V3.0.2 Build 140126

Note:

Auxiliary here indicates Spot Output DS-7200HWI-SH, DS-7300HWI-SH: V2.2.8 Build 130902

| Model | | NVR | | | DVR | |
|--|-----------|----------------|---|--|--|--|
| | | 8107 | Netra | KY2013 | Netra | |
| | | DS-7604NI-SE/P | DS-7716NI-SP/16 -9600NI-ST/RT | DS-7200HWI-SH DS-7300HWI-SH | DS-9000HFI-ST | DS-9000HWI-ST |
| Video Output Interfaces | | VGA, HDMI | VGA, HDMI, Main BNC | VGA, HDMI, Main BNC | VGA, HDMI, Main BNC, Auxiliary | |
| Connect VGA before DVR/NVR launch | VGA/HDMI | Menu | Menu display selectable between VGA and HDMI | Menu | Menu display selectable between VGA and HDMI | Menu |
| | Main BNC | N/A | No menu, independent output, video display configurable | No menu, output same video display as VGA | No menu, independent video outputs, video display configurable | No menu, independent video outputs, video display configurable |
| | Auxiliary | | N/A | N/A | No menu, multiple video outputs, video display configurable | No menu, multiple video outputs, video display configurable |
| Connect VGA after DVR/NVR launch | VGA/HDMI | Menu | No menu, independent output, video display configurable | No menu, output same video display as Main BNC | No menu, independent output, video display configurable | No menu, output same video display as main BNC |
| | Main BNC | N/A | Menu | Menu | Menu | Menu |
| | Auxiliary | | N/A | N/A | No menu, multiple output, video display configurable | No menu, multiple output, video display configurable |
| Connect HDMI before DVR/NVR launch (Disconnect VGA) | HDMI | Menu | Menu, display selectable between VGA and HDMI | Menu | Menu, display selectable between VGA and HDMI | Menu |
| | Main BNC | N/A | No menu, independent output, video display configurable | No menu, output same video display as HDMI | No menu, independent output, video display configurable | No menu, independent output, video display configurable |
| | Auxiliary | | N/A | N/A | No menu, Multiple output, video display configurable | No menu, Multiple output, video display configurable |
| Connect HDMI after DVR/NVR launch (Disconnect VGA) | HDMI | Menu | No menu, independent output, video display configurable | No menu, output same video display as Main BNC | No menu, independent output, video display configurable | No menu, output same video display as main BNC |
| | Main BNC | N/A | Menu | Menu | Menu | Menu |
| | Auxiliary | | N/A | N/A | No menu, multiple output, video display configurable | No menu, multiple output, video display configurable |